

Retroreflective Light Barrier RLR / ISN / ISD - 2/4/6-XC-GD

ISD-2/4/6XC-GD



Housing M30

ISN-2/4/6XC-GD


II 2G Ex d IIC T6 Gb
II 2D Ex tb IIIB T100°C Db IP67

- Long range
- Type ISD, applicable in Ex Zones 1, 2, 21, 22
- Type ISN, applicable in Ex Zones 2, 22
- Robust sensor for industrial applications


II 3G Ex nA IIB T4 Gc
II 3D Ex tc IIIA T135°C Dc IP67

Technical Data	Type	RLR-2/4/6XC	ISN-2/4/6XC-GD	ISD-2/4/6XC-GD
Type of Ex protection, Gas, at 94/9/EG		None	II 3G Ex nA IIB T4 Gc	II 2G Ex d IIC T6 Gb
Type of Ex protection, Dust, at 94/9/EG		None	II 3D Ex tc IIIA T135°C Dc IP67	II 2D Ex tb IIIB T100°C Db IP67
Applicable in Ex Zones		None	Zones 2, 22	Zones 1, 2, 21, 22
Range (adjustable) (on reflector D=83mm)			IS./RLR-2XC(-GD) = 2m IS./RLR-4XC(-GD) = 4m IS./RLR-6XC(-GD) = 6m	
Response time			IS./RLR-2/4XC(-GD): 5ms, IS./RLR-6XC(-GD): 1ms	
Light source			visible red, 623nm	
Beam pattern (at a distance of 2m)			appr.12°	
Supply voltage			24VDC ±15%	
Absolute maximum input voltage Um			30VDC	
Maximum current consumption		IS./RLR-2/4XC(-GD): 45mA, IS./RLR-6XC(-GD): 50mA		
Maximum power dissipation		IS./RLR-2/4XC(-GD): 1.24W, IS./RLR-6XC(-GD): 1.38W		
Output, series RLR/ISN/ISD-2/4XC(-GD)			1 x PNP, short circuit protected, maximum 100mA	
Output, series RLR/ISN/ISD-6XC(-GD) and S181			1 x Push-Pull, short circuit protected, maximum 100mA	
Output impedance			appr.15Ω	
Pollution indication output VA			1 x PNP, short circuit protected, maximum 100mA	
Emitter disable input, only types ...-DI			PNP compatible, R _i =10kΩ	
Housing			M30, yellow brass, nickel plated, 6XC with additional optic	
Enclosure rating, at EN 60529		IP 54	IP67	IP67
Shock and vibrating resistance			Vibration: 30g over 20Hz to 2kHz. Shock:50g for each direction (X, Y, Z)	
Operating temperature range T _{amb}			-20°C < T _{amb} < +60°C	
Connection cable		4 + PE x 0,5mm ² , TPU, oil resistant, shielded, leads numbering marked, L=3m		
Connection cable, types xxx--DI		6 + PE x 0,5mm ² , PVC, shielded, leads numbering marked, L=3m		
Socket, types RLR/ISN-2/4/6XC S99			Socket M12, Lumberg type RSF 5, 5 terminals	
Accessories included, all types			- 2 nuts M30 (or 1 clamp, on request)	
Accessories included, only ISN and ISD			- 1x Spare safety screw with packing ring for potentiometer sealing	
Accessories, included, only ISN-2/4/6XC-GD S99			- 1x Safety lock device, mount at the cable connection, for locking the connection (black synthetic device) - 1x Warning plate "WARNING - Explosion Hazard - Do Not Disconnect While Circuit Is Live Unless Area Is Known To Be Non-Hazardous", self-sealing, for gluing on the cable connector	
Accessories, not included only RLR/ISN-2/4/6XC(-GD) S99			- Cord Set Lumberg RKTS 5-298/xx (straight type), or RKTW/RKWTW 5-298/xx (right angle type)	
Options			- Switching frequency: - Cable length: - ISD-2/4XC-GD S43: - RLR/ISN-2/4XC(-GD) S99: - RLR-2/4XC S109: - RLR/ISN/ISD-..XC(-GD) S147: - RLR/ISN/ISD-2/4XC(-GD) S181: - RLR/IS-2/4/6XC(-GD)-DI: - RLR/ISN/ISD-6XC(-GD) S218:	Up to 2kHz, on request Up to 100m, on request With additional optic Socket M12, Lumberg RSF 5, 5 pins Working temperature range -20°C to +100°C Special gluing of the lenses With push-pull output With emitter disable input (not for types S99) Low profile lens for use with aeration tube
Function Output and display			 Light beam interrupted LED shows red	 Light beam reflected by the triple mirror LED shows green or yellow
Function at standard supply voltage wiring:				
	Cable	Socket		
+24VDC	1	1	1/1= +20-28VDC	1/1= +20-28VDC
0V	2	3	PNP=OFF R 15Ω	PNP=ON R 15Ω
Output	3	4	3/4 = Out	3/4 = Out
Pollution indication output	4	2	NPN=ON (Only ...-6XC and ...-2/4XC S181)	NPN=OFF (Only ...-6XC and ...-2/4XC S181)
Disable input (only.-DI)	5	--	2/3 = 0V	2/3 = 0V
NC (to connect at 0V)	6	--		
PE	yel-grn	5		
Cable shield	white	--		
Function at reversed supply voltage wiring:				
	Cable	Socket		
+24VDC	2	3	2/3= +20-28VDC	2/3= +20-28VDC
0V	1	1	PNP=ON R 15Ω	PNP=OFF R 15Ω
Output	3	4	3/4 = Out	3/4 = Out
Pollution indication output	4	2	NPN=OFF (Only ...-6XC and ...-2/4XC S181)	NPN=ON (Only ...-6XC and ...-2/4XC S181)
Disable input (only.-DI)	5	--	1/1 = 0V	1/1 = 0V
NC (to connect at 0V)	6	--		
PE	yel-grn	5		
Cable shield	white	--		

Dimensions	145	IS.-2/4XC	IS.-2/4XC-DI
Connection layout			
RLR / ISN / ISD:			
LED	30	1	1
Potentiometer with dustproof packing screw	110	2	2
		3	3
		4	4
		--	5
		yellow-green	yellow-green
Dimensions	145	pin	cable color
Connection layout			
RLR / ISN.. S99:			
IRN: Dust protection cap for the socket	13	+24VDC	1 brown
LED	30	0V	2 white
Potentiometer	110	Output	3 blue
IRN: With dustproof packing screw	M30 x 1.5	Pollution Out	4 black
		DI	5 grey
		PE	
Dimensions	145	139 / RLR: 119	139 / RLR: 119
ISD-2/4XC S43	30	69 / RLR: 49	79 / RLR: 59
ISN/ISD-6XC	20	20	30
RLR-6XC:	27		
LED	M30 x 1.5		
Potentiometer with dustproof packing screw			
Connection layout as for RLR / ISN / ISD			
....-DI (with optional Disable Input)			
Uin:	18V-28VDC, DI = +24V = Disable	DI	
Response time:	≤ 200us	+24V	
Hold time:	≥ 7.5ms, DI = 0V = Enable	Sensor enabled ≥ 7.5ms	
		DI = 24V	
		200us	
		Sensor disabled Output holds previous state	
		200us	
		Sensor DI = 0V ≥ 7.5ms	
ATEX related designations:			
CE 0158	Manufacturer with address		Electrical data according to the chart
Type ISD-..-GD:	II 2G Ex d IIC T6 Gb		EC certification number: BVS 10 ATEX E 130 X DEKRA
	II 2D Ex tb IIIB T100°C Db IP67		Declaration by manufacturer at 94/9/EC
Type ISN-..-GD:	II 3G Ex nA IIB T4 Gc		Date of production: numbers 5 to 8 of the serial number (year/week)
	II 3D Ex tc IIIA T135°C Dc IP67		Tamb: -20°C < Tamb < +60°C
Equipotential Bonding prescription for Ex Devices:			
			The end of the cable must be connected outside the hazardous location. Check the reliable, non-corrosive holding of the protection earth connection.
			The cable shield is to connect to PE in a wide area.
Operating Manual / EC-Declaration of Conformity:			
Mounting prescriptions	Sensors with disable input, types-XC-DI (Not for types S99/109):		
Ex Protection:	If several sensors are installed close to another, it is necessary to use sensors with disable input. By using the disable input DI, each sensor can be controlled in a short reaction time. If only one sensor is activated in the same time, a mutual influence is precluded.		
It is necessary to take into consideration the valid international and national rules and regulations (EN 60079-14). The maximum input voltage Um=30VDC must not be exceeded. The local equipotential bonding have to be done. The protective earth (PE) is solid connected with the housing. The cable has to be installed and protected against damages. The cable with termination fittings, or in cable tray systems and installed in a manner to avoid tensile stress at the termination fittings. To connect cables inside hazardous locations only use certificated Ex e housings. All cable terminals must be connected outside hazardous locations. Additional optical lenses are not allowed in hazardous locations. In dust Ex zones, do not operate the sensors without fixed dustproof sealing crew. After adjust the potentiometer, the dustproof sealing crew with undamaged packing ring, must be screwed down. Damaged or lost screws or packing rings must be replaced.	DI = 0V or not connected = emitter enabled DI = High (24VDC) = emitter disabled		
Type ISD-XC-GD: Applicable in Ex zones 1, 2, 21, 22.	For a correct function the sensor must be enabled for at least 7.5ms (DI=0V). If the DI input will be disabled, the outputs holds the previous output status from the last enabled time.		
Type ISN-XC-GD: Only applicable in Ex zones 2, 22.	The DI input is PNP compatible.		
Type ISN-XC-GD S99: Only applicable in Ex zones 2, 22. Do not separate the connector when the supply voltage is connected to the cable. When installing the sensor, the safety lock device must be fitted at the cable connector. The additional adhesive warning label must be fixed to the connector housing at the connection cable. Lumberg cordsets RKTS 5-298/xx (Straight type) or RKWTH 5-298/xx (Right angle type), are allowed ONLY. It is necessary to take into consideration the mounting prescription of the connector manufacturer. In dusty locations, the protection cap for the sensor socket must be fitted, when no connection cable is connected.	Maintenance For a high reliability hold the lens and the mirror free from sediment. No special maintenance is required. If the lens or the mirror becomes dirty, they should be cleaned with a non-aggressive cleaning liquid. Equipment must only be repaired by the manufacturer.		
General mounting prescriptions:	General safety instructions Series ISN-XC-GD S99: "WARNING - EXPLOSION HAZARD - WHEN IN HAZARDOUS LOCATIONS, TURN OFF POWER BEFORE REPLACING OR WIRING MODULES. DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NONHAZARDOUS". The mounting of the sensor in dusty locations without fixed cordset or protection cap results in a high ignition risk. The sensors must not be used for Accident-Prevention! In worst case the output can change to any state! When installing and operating with the sensor, it is necessary to take into consideration the relevant international and other national regulations:		
The electrical connections must be exactly as shown in the connection diagram. The cable shield must be connected short. The cable shield should be connected to the protection earth, large-surfaced. Connection cables must not be installed parallel to high voltage cables. Do not exceed the maximum ratings.	EN 60079-14, ATEX 118a, single directive 1999/92/EC. The sensor and the fibre optic are conform to the following standards: EN 60079-0:2009, EN 60079-1:2007, EN 60079-15:2010, EN 60079-31:2010, EN 60825-1:2006; EN 60825-2:2004; EN 60529; EN 61000-4-2 to EN 61000-4-6, EN 61000-6-1/-2, EN 61000-6-4. Ex protection: 94/9/EC (ATEX 100a), Machine directive: 2006/42/EC, EMC: 2004/108/EC, RoHS: 2011/65/EU.		
Function	General Notes, disposal We reserve the right to modify our equipment. Our equipment is designed such way, that it has the least possible adverse effect on the environment. It neither emit or contain any damaging or siliconized substances and use a minimum of energy and resources. No longer usable or irreparable units must be disposed of in accordance with local waste disposal regulations.		
The sensor can only be driven with a retroreflector. Only 3 times broken light beams will be detected. The sensor works basically as light barrier on reflective mirrors. If the sensor detects reflected light, the output switches to +24VDC or 0V dependent of the polarity of the supply voltage. If the sensor works under safe conditions the LED shows green. If the sensor detects only poor reflected light, the LED shows yellow and the pollution indication output VA switches to +24VDC. If no reflected light will be recognized, the LED shows red, the outputs switches to 0V and the control-output is switching OFF. The load on the output must be connected to 0V.	EC-Declaration of conformity Model ISD: EC-Type Examination Certificate. No. BVS 10 ATEX E 130 X. Model ISN: ATEX declaration by manufacturer at 94/9/EC. ATEX certification of quality type production of Ex devices at the directive 94/9/EC, CE 0158. Certification No: BVS 03 ATEX ZQS / E118. The conformity of the devices with the EC standards and directives and the EC-type examination certificate and the observation of the Quality Safety System ISO 9001:2008 with the ATEX module "Production", declares:		
Potentiometer adjustment	Hans Bracher, Matrix Elektronik AG		
For the detection of thin, transparent films, it is necessary the potentiometer by the following procedure:			
- Mount the sensor and the mirror.			
- Turn the potentiometer left to the sensor is switching off.			
- Turn the potentiometer right just to the sensor is switching on.			
- Check the safe function of the sensor. The output must works without any output delay. If a delayed function of the output / LED is recognized, turn the potentiometer a little more to the right side.			